

Tinytag View 2 Current Logger (0 to 200A AC)

TV-4810

Issue 4
17th October 2014
E&OE

The TV-4810 measures current from 0 to 200A AC and is ideal for mains and power consumption monitoring.

As well as recording data the unit has a display that shows what the unit is currently reading. The unit has an IP65 case and features high reading resolution and accuracy, a large memory, a fast offload speed and a low battery monitor.

This unit is supplied with a current clamp suitable for conductor sizes up to 20mm.



Popular Applications

- Mains Monitoring
- Power Consumption Monitoring

Features

- 0 to 200A AC Current data logger
- LCD display of current readings
- 30,000 reading capacity
- High Accuracy
- High Reading Resolution
- Fast Data Offload
- 2 user-programmable alarms
- Low battery monitor
- User-replaceable battery





Features

Total Reading Capacity	30,000 readings
Memory type	Non Volatile
Display	4 digits + indicators
Display Refresh Rate	Every 2 seconds
Trigger Start	Magnetic Switch
Delayed Start	Relative / Absolute (up to 45 days)
Stop Options	When full After n Readings Never (overwrite oldest data)
Reading Types	Actual, Min, Max
Logging Interval	1 sec to 10 days
Offload	While stopped or when logging in minutes mode
Alarms	2 fully programmable; latching

Reading Specification

Reading Range	0.15 to 200A AC
Frequency Range	40Hz to 10kHz
Maximum Current	240A AC*
Reading Resolution	10mA
Display Resolution	0.1A
Accuracy	0.5A to 10A (5% of reading +/-0.5A) 10A to 40A (3% of reading +/-0.5A) 40A to 200A (2% of reading +/-0.5A)

*The measuring time between 200 and 240A should be limited to 10 minutes on, followed by 30 minutes off.

Physical Specification

Data Logger (TV-4810)

Operational Range*	-30 °C to +70 °C
Case Dimensions	
Diameter	60mm / 2.36"
Length	85mm / 3.35"
Width	77mm / 3.03"
Depth	35mm / 1.38"
Weight	85g / 3oz

*The Operational Range stated above indicates the physical limits to which the unit can be exposed.

Current Clamp (ACS-0003)

Operational Range**	-10 °C to +55 °C (14 °F to +131 °F)
Clamp Dimensions	
Length	135mm / 5.31"
Width	35mm / 1.38"
Height	65mm / 2.56"
Weight	180g / 6.35oz
Lead Length	1.5m
Conductor Size	20mm (maximum)

**The Operational Range stated above indicates the physical limits to which the clamp can be exposed.

Notes

Battery Type Tekcell SBAA02P;
 SAFT LS14250 or LST14250

The logger will operate with other 1/2AA 3.6V Lithium (Li-SOCI2) batteries but performance cannot be guaranteed.

Replacement Interval Annually

Before replacing the battery the data logger must be stopped.

After removing an old battery from a logger, wait five minutes before inserting the new one.

Data stored on the logger will be retained after a battery is replaced.

The clarity of the display may change at extremes of temperature.

If used at low temperatures the data logger should be allowed to warm to room temperature before it is opened to avoid condensation forming inside the unit.

Calibration

This unit is configured to meet Gemini's quoted accuracy specification during its manufacture.

We recommend that the calibration of this unit should be checked annually against a calibrated reference meter.

A certificate of calibration, traceable to a national standard, can be supplied for an additional charge either at the point of purchase, or if the unit is returned for a service calibration.

Approvals

Gemini Data Loggers (UK) Ltd. operates a Business Management System which conforms to ISO 9001 and ISO 14001.



Required and Related Products

To use this data logger you will require the following software:

SWCD-0040: Tinytag Explorer software

and a

CAB-0007-USB: Tinytag Ultra/Plus/View USB Download Cable

The SWCD-0040 software and CAB-0007-USB cable can be ordered together in a pack using the part number SWPK-7-USB.

Further Related Products

SER-9500: Tinytag Data Logger Service Kit
ACS-5000: Tinytag Alarm Box
ACS-6000: Trigger Start Magnet